

# Potentiometer 7mm With Power Switch

## **TP76N00N**

#### **Feature**

• Extremely Slim & Small size (7mm)

## **Application**

- Car audio
- Audio equipment
- Communication radio switch and volume



## **Specifications**

#### Potentiometer

1 Ottillometer	
Operating Temperature Range	-20 to 70
Rated Power	0.05W
Maximum Operating Voltage	10V DC, 50V AC
Total Rotation Angle	300+/-5 °
Resistance value range	2K ~ 1M
Total Resistance Tolerance	+/-20%
Resistance Taper	A, B
Rotating torque	2.0 ~ 20.0 mNm
Life	15,000 cycles

#### Switch

Switch circuit	Rotary Switch SPST
Rated voltage and current	16V DC 3.0A
Operation angle	50 ° max.
Operating torque	78.4mN/m max.
Life	10,000 cycles min.