



## Potentiometer 7mm with Switch

### TP76N1034N

#### Feature

- Extremely Slim & Small size (7mm)

#### Application

- Car audio
- Audio equipment
- Communication radio switch and Volume



#### Specifications

##### Potentiometer

Operating Temperature Range	-20 to 70
Rated Power	0.05W
Maximum Operating Voltage	10V DC, 50V AC
Total Rotation Angle	300+/- 5 °
Resistance value range	2K ~ 1M
Total Resistance Tolerance	+/- 20%
Resistance Taper	A, B
Rotating torque	9.8 ~ 49.0 mNm
Life	15,000 cycles

##### Switch

Switch circuit	Rotary Switch SPST
Rated voltage and current	16V DC 3.0A
Operation angle	50 ° max.
Operating torque	78.4mN/m max.
Life	10,000 cycles min.